
Loading and saving session from and to a USB key on your DiGiCo console

Loading SD Sessions that contain Waves MultiRack session from a USB drive

When you load a session from a remote USB drive that is plugged into the console, the SD software will prompt you to save the session to Drive D. This prompt is displayed while MultiRack is still loading its plug-in session.

Trying to save the session while MultiRack is loading will not result in MultiRack saving the session. Again, the session will not be saved!

To avoid this error, simply wait until MultiRack's progress bar indicates that the session has been fully saved, and then save to Drive D as usual.

Removing the USB drive from the USB port

Further more to the above, if you remove your USB drive from the console's USB port before saving the SD and MultiRack session to Drive D, MultiRack's auto-save function will attempt to save the session to the USB drive which it remembers but which is now not present. This will cause a MultiRack error following which MultiRack will re-launch and load a blank session causing an audio mute.

To avoid this behaviour, simply save the SD session to Drive D and then remove the USB drive.